

# Growatt ShineLink-X

- Cable free, easy installation
- Dynamic IP, plug and play
- Communication distance up to 120m
- Support up to 3 devices
- Built-in memory for up to one month of data
- Online monitoring and maintenance



P O W E R  
- I N G O  
T O M O -  
R R O W O

**GROWATT**

[www.ginverter.com](http://www.ginverter.com)

Datasheet	ShineLink-X
<b>Communication Interface</b>	
RF433	Yes
RF433(No barrier wall)	Up to 120 m
RF433(two walls blocking)	20 m
<b>Power Supply</b>	
Power consumption	<2W standby, <5W peak
Voltage range	196V~250V
Frequency	50/60Hz
<b>General Specifications</b>	
Dimensions(L/W/H)	105/85/26mm
Weight	< 1kg
Mounting options	Tabletop/wall-mount
Protection degree	IP30
Display	LED
Ambient temperature range	-20 to 65 °C
Humidity	0-95% (non condensing)
<b>Features</b>	
Remote firmware upgrade	Yes
Max. number of devices to monitor	3(RF433)
CE	